




Model: PPBCHA20



- 1, USB-A1 QC3.0 Output
- 2, USB-A2 QC3.0 Output
- 3, Type-C1 PD 100W Input & Output
- 4, Type-C2 PD 45W Input & Output
- 5, Power Button
- 6, LED Power display



Model: PPBCHA20
 Battery Capacity:30000mAh Li-ion(1111Wh)
 Type-C1 PD Input & Output: 100W DC 5V/3A,9V/3A, 12V/3A, 15V/3A, 20V/5A
 Type-C2 PD Output: 45W DC 5V/3A,9V/3A, 12V/3A, 15V/3A
 USB-A1&2 QC3.0 Output: DC 5V/3A, 9V/2A, 12V/1.5A
 SCP : DC 5V/4.5A, 4.5V/3A (22.5W Max)
 Total Output: 110W Max
 Type-C1+C2: 65W + 45W
 Type-C1+USB-A1 or A2: 65W + 22.5W
 Type-C1+C2+USB-A1 or A2: 65W + 20W + 22.5W
 Type-C2+USB-A1 or A2: 45W + 22.5W
 Type-C2+USB-A1+USB-A2: 45W + 15W
 Type-C1+C2+USB-A1+A2: 65W + 20W + 15W
 Dimension: 150*55*48MM
 Weight: about 577g

To recharge your power bank, using the Type-C cable to connect it to a computer, car-charger or wall-charger and then the power bank would get charged automatically, the LED digital display will indicate the current power and the next power indicator will flash.

Using your device's charging cable (not included), connect your device to the USB outputs or Type-C output, click on the power button one time, the LED digital display will show the current power, then the power bank will start charging your device, indicate your power bank's remaining charge. After finished the charging you can press the button for twice to turn it off or it would be turned off automatically without working after around 35 seconds.

With digital display
Three fast charging output ports can supply power to different equipment at the same time.
The maximum power reaches 100W, which is compatible with most laptops on the market
Compatible with charging protocols of various fast charging products on the market
Rubberized coating
High transfer efficiency
Li-ion battery cell with high safety and stability
Low self-discharge; Long time standby
High compatibility fits for different mobile phones
Intelligent protect program to avoid overcharging / discharging, short circuit, etc
Private and compact design, easy operation
Power bank size:150*55*48mm


1. Never leave a charging battery unattended.
2. Do not expose the power bank to excess humidity or liquids. It should be stored in a cool, dry place when not in use.
3. Do not damage or puncture the casing of the power bank. This may cause over-heating, fire or an explosion.
4. Do not expose the power bank to sources of heat, including radiators, stoves, or fires. Do not expose to ambient temperatures above 40°C, such as in a car on hot day, or in direct sunlight. Failure to do so may cause over-heating, fire, or explosion.
5. Do not use in a strong electrostatic or electromagnetic environment including near microwaves as this may shorten the device's life.
6. If the power bank emits an odour, excessive heat or becomes discoloured or distorted, please discontinue use immediately.
7. Refer all servicing to qualified service personnel, which is required if power bank is damaged in any way, is exposed to liquid or does not operate normally. Please do not attempt to service or open the device. This may cause over-heating, fire or an explosion.
8. At the end of the device's life, please dispose of this product at a battery recycling station. It is not suitable for domestic waste disposal.
9. If a new power bank is not used for a period of three months or more, its battery capacity will be reduced, but will restore to normal capacity after 3-4 charge and discharge cycles.

Designed and produced by Teqtronix International Inc.
All rights reserved 2023. Made in China

For more information, please contact our support team
hey@powerology.me



f powerology @ powerology.me



شحن سريع بأربعة أجهزة



Model: PPBCHA20



١. لا تترك بطارية شحن بدون رقابة،
٢. لا تعرض تلك البطاقة لأي ظروف أو السوائل الزائدة، يجب تخزينها في مكان بارد وجاف عندما تكون قيد الاستعمال،
٣. لا تقرب أو تلمس أقطاب تلك البطاقة، قد يتسبب ذلك في ارتفاع درجة الحرارة أو حدوث انفجار،
٤. لا تعرض تلك البطاقة لمصادر الحرارة، بما في ذلك المشعات أو السخانات أو الحفنة، لا تعرض درجات الحرارة بحسبة تزيد عن ٤٠ درجة مئوية، كما هو الحال في السيارة في يوم حار أو في الشمس المباشرة، يجب عدم القيام بذلك في ارتفاع درجة الحرارة أو حدوث انفجار أو حدوث انفجار،
٥. لا تستخدم بطارية ليثيوم الكبريت وثنائية أكسيد الكبريت مغناطيسية قوية، بما في ذلك أجهزة الميكروويف، الثلاجة إلخ هذا قد يقصر من عمر الجهاز،
٦. لا تلمس أو تلمس تلك البطارية راحة أو تغير لونها أو تغير شكلها، يرجى التوقف عن استخدامها على الفور،
٧. لا يراعى جميع ألامن الصلبة إلى مواضع التخزين الموصلة، وهو أمر مطلوب في حالة تلف تلك البطارية أو شكل من أشكالها، أو تعرضه للسوائل أو لا يعمل بشكل طبيعي، يرجى عدم محاولة صيانة الجهاز أو فتحه، قد يتسبب ذلك في زيادة السخونة أو حدوث انفجار أو حدوث انفجار،
٨. في نهاية عمر الجهاز، يرجى التخلص من هذا المنتج في محطة إعادة تدوير البطاريات، إنه غير مناسب للتخلص من النفايات المنزلية،
٩. إذا لم يتم استخدام بطارية جافة لمدة أربعة أشهر أو أكثر، فيستحسن تقليل سعة بطاريتها،
١٠. يمكن استبدال سعة البطارية بالصيغة بعد ٤-٣ سنوات، ومزيد.

تتم تصميمها وتصنيعها بواسطة شركة
جميع الحقوق محفوظة © ٢٠٢٣

لمزيد من المعلومات، يرجى الاتصال بفريق الدعم لدينا:
support@porodo.net



f powerology **@** powerology.me


اشحن باور بانك الخاص بك

لإعادة شحن تلك البطارية الخاص بك ، استخدم كبل تايب-سي لتوصيله بجهاز كمبيوتر أو مشاحن سيارة أو شاحن حائط ثم نهم شحن باور بنك ثلاثيًا ، وستشير شاشة LED الرقمية إلى الطاقة الحالية ومؤشر الطاقة التالي ، سوف الرماد.

بإستخدام كابل نحس جهازك (غير مدرج)، قم بتوصيل جهازك بمخرجات يو أس بي أو مخرج
 آي-إيس-بي، واضغط زر الطاقة مرة واحدة، وستظهر شاشة LED الزرقاء الطاقة الحالية. ثم
 سيبدأ بنك الطاقة في شحن جهازك، تشير إلى الشحن المتبقي لبنك الطاقة الخاص بك، بعد
 الانتهاء من الشحن، يمكنك الضغط على الزر مرتين لإيقاف تشغيله أو سنبين لإيقاف تشغيله
 تلقائياً بعد ٣٠ ساعة.

مع شاشة رقمية
تضمن ثلاثة منافذ إخراج سريعة الشحن توفير الطاقة لمعدات مختلفة في نفس الوقت
يمكن للبطارية القصوى أن تداوم، وهو متوافق مع معظم أجهزة الكمبيوتر المحمولة في السوق
المتوافق مع بروتوكولات الشحن المختلفة منتجات الشحن السريع في السوق
كفاءة نقل عالية
خليفة صارية لينتجوه، أين ذات أمان واستقرار عاليين
انخفاض التفرغ الذاتي وقت طويل في وضع الاستعداد
التوافق العالي للأجهزة المحمولة المختلفة
برنامج حماية عالي لتجنب الشحن الزائد/التفريغ، ماس كهربائي إلخ
تصميم خاص ومدمج، عملية سهلة
حجم: ٨٨ × ٥٥ × ١٠ ملم
مجموعات تلك الطاقة: ٥٠٠٠ ملجم

١. خرج USB-A QC^{3.0}
٢. خرج USB-A QC^{3.0}
٣. تايپ-سي ابي دي ١٠ وات الإدخال والإخراج
٤. نوع-سي ابي دي ٤٥ وات الإدخال والإخراج
٥. زر الطاقة
٦. شاشة LED للطاقة

[illegible]