



Powerology

6-MIC Hybrid ANC and ENC True Wireless Buds

SKU: PWLAU010

Table of Contents

Package Contents	2
First Use	2
Connection Method	2
Touch Button Function	3
Charging the Earbuds	3
Charging the Case	4
Instructions for Use	4
Voice Assistant	5
BEAST™ Mode	5
ANC ENx™ Technology	6
Smart Power Off	6
Manual Power Off	6
Specifications	7
Safety Caution	8
Warranty	9
Contact Us	9

Before installing and using the product, please carefully read this User Manual to guarantee correct usage and keep it secure for future reference.

Package Contents

A pair of TWS earbuds
One charging case
One USB type-C charging cable

First Use

Step 1: To activate your earbuds, simply open the lid of the charging case while the earbuds are inside. The earbuds will automatically power up, connect, and enter pairing mode. Alternatively, press and hold the multifunctional touch button on both earbuds for 3 seconds to manually power them on.

Step 2: Once powered on, the earbuds will switch to Connection mode, indicated by flashing red and blue lights.

Connection Method

- Enable Bluetooth on your phone or media device and initiate a search.
- Search for 'PWLAU010' and pair your device via Bluetooth.
- 3. To manually pair the earbuds if they are not in pairing mode, press the right earbud button six times. A successful pairing will be indicated by flashing red and blue lights.
- 4. Once turned on, PWLAU010 will automatically reconnect to previously paired devices within range.

Notes:

1. The pairing mode remains active for 3 minutes, after which the earbuds will automatically power off if not paired.

2. If you do not complete pairing within this time, you will need to restart the earbuds and repeat the pairing process.

Touch Button Function

Tapping 4 times

Tap the touch area on the left earbud four times to activate the default smart voice assistant.

Tap and hold for 3 seconds

Press and hold the touch area on the left and right earbud for 3 seconds to manually power on the earbuds.

Tapping 4 times

Tap the touch area on the left earbud 4 times to enable Beast mode for enhanced audio performance.

Tap and hold for 5 seconds

Press and hold the touch area on the left and right earbud for 5 seconds to manually power off the earbuds.



Charging the Earbuds

Step 1: Insert the earbuds into the charging case ensuring they are properly aligned and close the lid.

Step 2: The charging case automatically powers down to conserve energy once the earbuds are fully charged, and the red indicator light will turn off.

Note: Please fully charge the earbuds before their first use. Ensure the charging case lid remains closed during charging to optimize the charging process.

Charging the Case

To charge the case, connect one end of the included USB Type-C cable to the case, and plug the other end into a wall adapter, power bank, or similar power source.

Casing LED Light Guide:

Battery Capacity	LED State
More than 20 %	Solid blue light remains on for 8 seconds when the case lid is opened or closed while earbuds are inside the case.
Less than 20 %	The blue light slowly flashes every 60 seconds when the case lid is opened or closed.
Case is in charging mode	The red light flashes continuously.
Case is fully charged	Solid red light remains on.
Earbuds are charging	The blue light flashes once and remains solid for 40 seconds before turning off.



Instructions for Use

Answer Calls: Double tap the multifunction touch button on the left or right earbud to answer an incoming call.

Reject/Hang Up Calls: Press and hold the multifunction touch button on the left or right for 2 seconds to reject an incoming call.

Play/Pause Music: Tap the multifunction touch button on the left or right earbud to control the music playback.

Next Track: Tap the multifunction touch button on the right earbud 3 times to skip to the next song.

Previous Track: Tap the multifunction touch button on the left earbud 3 times to skip to the previous song.

Note: Volume can be controlled only via the phone/media device.



Voice Assistant

Step 1: Tap the left multifunctional touch area four times to activate the voice assistant.

Step 2: Once activated, the voice assistant interface appears along with an audio prompt, allowing you to issue commands effortlessly.

* Suggested Commands:

"What is the weather today?"

"Play a song"

"Set a reminder"

Note: If the voice assistant is not activated, ensure that the feature is enabled in the settings of your connected device.

Step 3: Tap the left touch button four times to exit the voice assistant.



BEAST™ Mode

Tailored for gaming enthusiasts, BEAST™ Mode significantly enhances your gaming experience by reducing latency, ensuring smoother, more synchronized audio playback during games.

- 1. Tap the right earbud's touch button 4 times to activate Low Latency Gaming Mode, referred to as BEAST™ Mode. You will receive an audio confirmation once activated.
- 2. To turn off BEAST™ Mode and revert to Standard Music Mode, triple tap the right earbud's touch button.

ANC ENx™ Technology

The integrated ANC and ENx™ technology algorithm effectively eliminates background noise, providing over 40dB of noise cancellation to enhance your listening experience.

A. ANC Mode:

Press and hold either earbud for three seconds to cycle through the modes: ANC Mode, Transparent Mode, and Normal Mode.

B. Voice Clarity:

Experience crystal-clear voice calls without needing to activate the technology manually. The ENx™ mode is featured by default to ensure your voice is delivered uninterrupted in any setting—from busy streets to noisy workspaces.

Smart Power Off

- After using the earbuds, gently remove them from your ears.
- 2. Place the earbuds back into the charging case, ensuring they are correctly oriented, and then close the case lid.
- 3. Once securely placed in the case, the earbuds will automatically power off and commence charging.

Manual Power Off

- 1. Press and hold either earbud's touch control for 5 seconds to manually turn off the earbuds.
- 2. After the earbuds are powered off, place them back into the charging case and close the lid securely.

Specifications

Battery Capacity	350mAh (Charging Case), 35mAh (Earbuds)
Playtime	Up to 6H at 60 % Volume
Standby Time	50H
Recharge Time	1.5H (Charging Case), 1H (Earbuds)
Charging Port	Type-C
Driver Size	13mm x2
Low Latency	50ms
Bluetooth Version	V5.3
Bluetooth Name	PWLAU010
Water Resistant	IPX4
Transmission Range	10М
Frequency	20Hz to 20KHz

Charging Precautions		
1) Charger/Brick/Adapter	5V 2A	
2) Cable/Wire	Standard Cable (35 strands @ 0.10mm diameter/ strand)	

7

Safety Caution

- Follow the provided instructions for smooth operation of the earbuds.
- 2. Avoid using the earbuds in extreme temperatures.
- 3. Do not use the earbuds in water.
- 4. Keep the earbuds away from direct heat sources to prevent damage.
- 5. Avoid obstructing or forcing objects into the ports, such as the charging or LED indicator ports.
- 6. To protect your hearing and prolong the lifespan of the earbuds, it is advisable to use them at a volume below the maximum level.
- 7. The earbuds may initially start at maximum volume. Adjust the volume to a comfortable level using the controls on your phone or media device for a better listening experience.



Warranty

Products that you buy directly from our **Powerology** website or shop come with a 24-month warranty.

The 24-month warranty applies to products purchased directly from our **Powerology** website or store. If **Powerology** products are bought from any of our verified retailers, then the product is eligible for only a 12-month warranty. To extend your product's warranty, visit our website **powerology.me/warranty** and fill in your details in the provided form along with an uploaded picture of the product to process your request. Once approved, you will receive a confirmation email of the extended product warranty. Upload the required information within 48 hours of purchase to be eligible for a 24-month warranty period.

For more info, please check: powerology.me/warranty



If you have any questions about this Privacy Policy, please contact

us at: hey@powerology.me

Website: powerology.me

Instagram: powerology_official

Facebook: powerology.ME